

Specifications/Technical data (subject to change without prior notice):

| CW-200E DUO 2 in 1 electric comb & wire binding | |
|---|--|
| Max. punching capacity, paper | 25sheets(80gsm/20lbs) for comb 20sheets(80gsm/20lbs) for wire |
| Max. punching capacity, plastic foils | 2sheets(0.25mm/10mil) |
| Punching margin control(for comb only) | 2mm - 6mm (3/32" – 1/4") |
| Binding capacity, comb | Max. comb size: 51mm (2") for, 450sheets |
| Binding capacity, wire | Max. wire size: 16mm(5/8"), for 135sheets |
| Max. width of paper | A4, Letter and extra large size |
| Punching slots | A4 size: 21 for comb, 34 for wire Letter size: 19 for comb, 32 for wire |
| Adjustable paper stop | Yes |
| Net weight | 20kgs (44lbs) |
| Dimensions(W x D x H) | 460 x 440 x 225mm (18" x 17" x 9") |
| Electrical | EU: 220V/50HZ, 0.65AMP/150W US: 110V/60HZ, 1.7AMP/190W |

Binding guide – comb

| Comb(mm/inch) | Sheets | Margin | Comb(mm/inch) | Sheets | Margin |
|---------------|--------|--------|---------------|--------|--------|
| 6mm 1/4" | 25 | 2 | 22mm 7/8" | 195 | 4 |
| 8mm 5/16" | 45 | 2 | 25mm 1" | 220 | 6 |
| 10mm 3/8" | 65 | 2 | 28mm 1-1/8" | 245 | 6 |
| 12mm 1/2" | 95 | 2 | 32mm 1-1/4" | 270 | 6 |
| 14mm 9/16" | 125 | 4 | 38mm 1-1/2" | 320 | 6 |
| 16mm 5/8" | 145 | 4 | 45mm 1-3/4" | 370 | 6 |
| 19mm 3/4" | 155 | 4 | 51mm 2" | 450 | 6 |

Binding guide – wire

| Wire(mm/inch) | Sheets |
|---------------|--------|
| 6mm 1/4" | 25 |
| 8mm 5/16" | 45 |
| 10mm 3/8" | 65 |
| 11mm 7/16" | 80 |
| 12mm 1/2" | 95 |
| 14mm 9/16" | 125 |
| 16mm 5/8" | 135 |

General Safeguards

- Place your binder on a stable surface.
- Use the machine only for its intended purpose of punching and binding paper and document covers according to the indicated specifications.
- Always test the machine with some scrap paper before punching the final document.
- Take care that there are no staples or such like in the documents to be bound.
- Empty the waste tray regularly.
- Lift the machine from the bottom, not the cover or the handle.
- Unauthorized maintenance is not allowed.
- Follow all warnings and instructions marked on the unit.

Electrical safeguards

- The binding machine should never be placed near or over a radiator, heat register or water.
- Always turn off and unplug the binding machine prior to moving, cleaning, servicing, or any other action other than normal operation.
- Do not operate the unit with a damaged power supply cord or plug.
- Do not operate if the unit has been exposed to rain or water.
- This unit is intended for indoor use only.
- Do not attempt to serve the unit yourself. Opening and/or removing covers could expose you to dangerous voltage points and/or other serious risks. This action will also void the warranty.



2-in-1 Binding Machine

Comb Binding + Wire Binding
Reliure Anneaux Plastique + Métal
Encuadernadora de Canutillo de plástico + Wire
Plastikbindung + Drahtbindung

