

## Specifications/Technical data (subject to change without prior notice):

WW-200E DUO 2 in 1 electric wire binding	
Max. punching capacity, paper	20sheets(80gsm/20lbs)
Max. punching capacity, plastic foils	2sheets (0.25mm/10mil)
Punching margin control(for wire 2:1 only)	2mm - 6mm (3/32" - 1/4")
Binding capacity	Max. wire size: 32mm(1-1/4"), for 280sheets
Max. width of paper	A4, Letter and extra large size
Punching slots	A4 size: 34 for 3:1, 23 for 2:1 Letter size: 32 for 3:1, 21 for 2:1
Adjustable paper stop	Yes
Net weight	20kgs (44lbs)
Dimensions(W x D x H)	460 x 440 x 190mm (18" x 17" x 7-1/2")
Electrical	EU: 220V/50HZ, 0.65AMP/150W US: 110V/60HZ, 1.7AMP/190W

### Binding guide

Wire(mm/inch)	Sheets	Margin	Wire(mm/inch)	Sheets	Margin
6mm 1/4"	25	2	16mm 5/8"	145	4
8mm 5/16"	45	2	19mm 3/4"	165	4
10mm 3/8"	65	2	22mm 7/8"	195	4
11mm 7/16"	80	3	25mm 1"	220	5
12mm 1/2"	95	3	28mm 1-1/8"	245	5
14mm 9/16"	125	3	32mm 1-1/4"	280	5

### General Safeguards

- Place your binder on a stable surface.
- Use the machine only for its intended purpose of punching and binding paper and document covers according to the indicated specifications.
- Always test the machine with some scrap paper before punching the final document.
- Take care that there are no staples or such like in the documents to be bound.
- Empty the waste tray regularly.
- Lift the machine from the bottom, not the cover or the handle.
- Unauthorized maintenance is not allowed.
- Follow all warnings and instructions marked on the unit.

### Electrical safeguards

- The binding machine should never be placed near or over a radiator, heat register or water.
- Always turn off and unplug the binding machine prior to moving, cleaning, servicing, or any other action other than normal operation.
- Do not operate the unit with a damaged power supply cord or plug.
- Do not operate if the unit has been exposed to rain or water.
- This unit is intended for indoor use only.
- Do not attempt to serve the unit yourself. Opening and/or removing covers could expose you to dangerous voltage points and/or other serious risks. This action will also void the warranty.



## 2-in-1 Binding Machine

Wire binding pitch 3:1 + 2:1  
Reliure Anneaux Métal Pas 3:1 + 2:1  
Encuadernación de wire paso 3:1 + 2:1  
Drahtbindung Teilung 3:1 + 2:1

