

# Specifications/Technical data (subject to change without prior notice):

| CW-200E DUO 2 in 1 electric comb & wire binding |  |
|---|--|
| Max. punching capacity, paper                   | 25sheets(80gsm/20lbs) for comb<br>20sheets(80gsm/20lbs) for wire           |
| Max. punching capacity, plastic foils           | 2sheets(0.25mm/10mil)  |
| Punching margin control(for comb only)          | 2mm - 6mm (3/32" – 1/4")   |
| Binding capacity, comb                          | Max. comb size: 51mm (2") for, 450sheets                                   |
| Binding capacity, wire                          | Max. wire size: 16mm(5/8"), for 135sheets                                  |
| Max. width of paper                             | A4, Letter and extra large size  |
| Punching slots                                  | A4 size: 21 for comb, 34 for wire<br>Letter size: 19 for comb, 32 for wire |
| Adjustable paper stop                           | Yes  |
| Net weight                                      | 20kgs (44lbs)  |
| Dimensions(W x D x H)                           | 460 x 440 x 225mm (18" x 17" x 9")   |
| Electrical                                      | EU: 220V/50HZ, 0.65AMP/150W<br>US: 110V/60HZ, 1.7AMP/190W                  |

## Binding guide – comb

| Comb(mm/inch) | Sheets | Margin | Comb(mm/inch) | Sheets | Margin |
|---------------|--------|--------|---------------|--------|--------|
| 6mm 1/4"      | 25     | 2      | 22mm 7/8"     | 195    | 4      |
| 8mm 5/16"     | 45     | 2      | 25mm 1"       | 220    | 6      |
| 10mm 3/8"     | 65     | 2      | 28mm 1-1/8"   | 245    | 6      |
| 12mm 1/2"     | 95     | 2      | 32mm 1-1/4"   | 270    | 6      |
| 14mm 9/16"    | 125    | 4      | 38mm 1-1/2"   | 320    | 6      |
| 16mm 5/8"     | 145    | 4      | 45mm 1-3/4"   | 370    | 6      |
| 19mm 3/4"     | 155    | 4      | 51mm 2"       | 450    | 6      |

## Binding guide – wire

| Wire(mm/inch) | Sheets |
|---------------|--------|
| 6mm 1/4"      | 25     |
| 8mm 5/16"     | 45     |
| 10mm 3/8"     | 65     |
| 11mm 7/16"    | 80     |
| 12mm 1/2"     | 95     |
| 14mm 9/16"    | 125    |
| 16mm 5/8"     | 135    |

## General Safeguards

- Place your binder on a stable surface.
- Use the machine only for its intended purpose of punching and binding paper and document covers according to the indicated specifications.
- Always test the machine with some scrap paper before punching the final document.
- Take care that there are no staples or such like in the documents to be bound.
- Empty the waste tray regularly.
- Lift the machine from the bottom, not the cover or the handle.
- Unauthorized maintenance is not allowed.
- Follow all warnings and instructions marked on the unit.

## Electrical safeguards

- The binding machine should never be placed near or over a radiator, heat register or water.
- Always turn off and unplug the binding machine prior to moving, cleaning, servicing, or any other action other than normal operation.
- Do not operate the unit with a damaged power supply cord or plug.
- Do not operate if the unit has been exposed to rain or water.
- This unit is intended for indoor use only.
- Do not attempt to serve the unit yourself. Opening and/or removing covers could expose you to dangerous voltage points and/or other serious risks. This action will also void the warranty.

GB

## 2-in-1 Binding Machine

Comb Binding + Wire Binding  
Reliure Anneaux Plastique + Métal  
Encuadernadora de Canutillo de plástico + Wire  
Plastikbindung + Drahtbindung

**intimus**  
MAIL, PARCEL & OFFICE

## CW-200E DUO

